

# BCM

## DC Battery Charger



- AA size battery charger
- Protection from overcharging, ensure long life span of the battery
- Efficient use of excess energy of PV system
- Charge up to 4 AA size batteries
- LED display "Charging on" and "off-Switch"
- Holder for DIN rail mounting available

BCM is an innovative charger for AA-Size rechargeable NiMeH and NiCd Batteries. It is specially designed for application in PV solar systems. In addition, it can be used together with any 12V Battery.

The AA-size batteries are charged over a small constant current which is kept on a low level to prevent any overcharging. Additional protection is given by the additional voltage limitation. Because of the special voltage and current limitation, the batteries are well protected against overcharging even if they are kept for longer time in the charger. The gentle charging process guarantees long life for your AA-size battery. BCM allows to charge up to four AA size batteries. Because each battery has got its own voltage limitation, it is possible to mix different types and sizes of rechargeable batteries. It is also possible to charge one, two three or four batteries at a time.

A new innovative feature is the use of excess energy management. By using this feature only the excess energy which cannot be taken over by the systems main battery, is used to charge the AA batteries. This way it is possible to increase the performance of the system.

Type	BCM
Nominal Input Voltage	12V
Input Voltage range	10.5V-15V
Nominal Output Voltage	4x1.5V
Max. charging Current (@1.35V)	<60mA
Charging time for 500mAh Battery	approx.14h
Charging time for 1000mAh Battery	approx.28h
Charging time for 1500mAh Battery	approx.42h
Charging time for 2500mAh Battery	approx.70h
Battery size	AA(in Europe called Mignon)
Battery types	NiMeH/NiCd
Battery capacity	500mAh-2500mAh
Dimensions	80x100x32mm
Weight	180g
Temperature range	-40 to +50 °C

Phocos AG, Germany  
info@phocos.com

Phocos China Ltd., China  
Info-china@phocos.com

Phocos India Solar Pvt. Ltd., India  
Info-india@phocos.com

Phocos Latin America S.R.L, Bolivia  
Info-latinamerica@phocos.com

Phocos Rep. Office Australia, Australia  
Info-australia@phocos.com

Phocos Rep. Office Brazil, Brazil  
Info-brazil@phocos.com

Phocos Rep. Office Eastern Africa, Kenya  
Info-easternafrica@phocos.com

Phocos Eastern Europe S.R.L., Romania  
Info-easterneurope@phocos.com

Phocos SEA Pte Ltd, Singapore  
Info-sea@phocos.com

Phocos Rep. Office South Africa  
Info-sadc@phocos.com

Phocos Tunisia  
Info-maghreb@phocos.com

Phocos USA  
Info-usa@phocos.com